

# Outdoor 44x10w RGBW 4in1 Led city color light Model:WCW-44



## User manual

Please read this manual carefully before use

# 1. Technical Specifications

**Light Sources:** 44\*10W 4in1 RGBW LED

Beam Angle: 30°

Power Voltage: AC 100-240V, 50/60Hz

Packing size & Weight: 60x39x23cm ,13.25kgs

## Control

DMX Channel: 4/8 Channel

Control Modes: DMX512, master, auto and sound

## Construction

Display: LCD Display

Data In/Out socket: IP65 3-pin XLR in and out

Power Socket: IP65 powercon in and out

Protection Rating: IP65

## 2. Menu instruction

NO	Display	Description
1	DMX-8CH D: 001	Address code (001-512), up down change codes
2	DMX-CH D: 4CH	8/4chs dmx channels choose, up down change channels
3	Jump D: 099	Colors jump change (00-99), Up down change speed
4	Gradient D: 099	Colors gradual change (00-99), Up down change speed

5	Color R D: 255	Red dimming (000-255)
6	Color G D: 255	Green dimming (000-255)
7	Color B D: 255	Blue dimming (000-255)
8	Color W D: 255	White dimming(000-255)

### 3. Control panel



**1. 4 digital number display:** Display menu functions and specification;

<b>MENU</b>	Main menu function selection/exit submenu
<b>▲ UP</b>	Select the previous menu/specs increment
<b>▼ DOWN</b>	Select the next menu/parameter decreasing
<b>ENTER</b>	Save/Enter the next menu

## 4. DMX Channels

4CH mode:

DMX channel	Value	Description
1	0~255	Red dimming,from dark to bright
2	0~255	Green dimming ,from dark to bright
3	0~255	Blue dimming ,from dark to bright
4	0~255	White dimming ,from dark to bright

8CH Mode:

DMX channel	Value	Description
1	0~255	Dimmer,from dark to bright
2	0~255	Strobe, from slow to fast
3	Function	0— 50: NO; 51— 100: Jump change 101— 150: gradual change 151— 255: pulse change
4	Speed	Speed from slow to fast
5	0~255	Red dimming,from dark to bright
6	0~255	Green dimming ,from dark to bright
7	0~255	Blue dimming ,from dark to bright
8	0~255	White dimming ,from dark to bright