

Public Address (PA) System 60W Mixer Amplifier with MP3/FM/Bluetooth FA-660M/FA-6120M/FA-6240M/FA-6350M/FA-6500M



Description:

The 6 Zone Mixer Amplifier with MP3&FM tuner and bluetooth, with rated power output from 60W, 120W,240W, 350W to 500W,

it is ideal for background music system.

It is all in one solution include pre amplifier and mixer power amplifier into one 19" 2U height unit, which is economy of high reliable performance.

Various inputs includes phone jack front panel) and Mic/Line input 2-3 (6.3mm phone jack rear panel), two aux inputs (RCA rear panel).

One RCA line output for external mixer or amplifier.

Mic1 override other sources input and with mute level control amplifier is design with complete protection of overload, short circuit and high temp to avoid any damage.

Suitable for applications in bank, mosque, school theme centers and shopping center

Features:

- Public address (PA) mixer amplifier.
- 6 zone mixer power amplifier.
- 19" rack mount amplifier of 2U height.
- Built-in MP3 player by USB & bluetooth and FM tuner.
- Rated outputs of 60W, 120W, 240W, 350W to 500W
- 6 zone speaker outputs of 100V.
- 4-16 Ohms output for low impedance speaker connection.
- Six zone speaker outputs with on/off button and zone status
- Three microphone inputs, two aux inputs and one line output.
- Mic1(6.3mm phone jack front panel) and Mic/Line input 2-3(6.3mm phone jack rear panel).
- Aux 1-2 inputs on rear panel by RCA.
- Mic1 mute with highest priority
- input and with mute level control
- Volume control for Mic1-3, Aux
- AC power and output level meters.
- Overload, short circuit and high temp protection
- AC 230V operation system and AC115

Public Address (PA) System 60W Mixer Amplifier with MP3/FM/Bluetooth FA-660M/FA-6120M/FA-6240M/FA-6350M/FA-6500M

Rear Panel:



Specification:

Model	FA-660M	FA-6120M	FA-6240M	FA-6350M	FA-6500M
Description	Public Address System 60W Mixer Amplifier				
Rated Power Output	60W	120w	240w	350w	500
Speaker Output	70V, 100V and 4-16Ω, 6 zone speaker out 100V				
Input	Mic1-3: 600 ohms(Ω) 5-8 mV, unbalanced, Line1-2: 10k ohms(Ω) 150-470 mV, unbalanced				
Frequency Response	60-15KHz				
THD	<0.5% at 1kHz, 1/3 rated power				
S/N Ratio	Line: 85 dB , MIC: >72 dB				
Protection	High temp, short circuit, overload protection				
Power Supply	AC230V or AC110V, 50-60Hz				
Power Consumption	100W	200W	400W	500W	600W
Dimension	484(W)×366(D)×88(H)mm				
Gross Weight	11kg	12.5kg	15kg	16kg	18.5kg
Warranty	5 years				