

PA Amplifier with USB/SD & FM & Blue Tooth

FA-30E/FA-60E/FA-120E



Features:

- Compact mini size public address amplifier
- Ideal for classroom sound system use
- Built-in 100V/70V transformer technology
- Tabletop amplifier with Mp3 player, FM radio & blue tooth
- Rate power output at 30W, 60W to 120W. Speaker output of 100V or 70V & 4Ohms-8 Ohms-16 Ohms
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- LED indicators for power, clip, protect and signal
- Mic1-3 and line 1-2 and telephone input. Mic1 of balanced XLR input with phantom power on rear panel. Mic2-3 microphone or line switchable unbalanced 6.3mm phone jack input. Line 1-2 input of RCA input and one RCA line output. Telephone input with VOX priority and MOH (Music on Hold).
- Volume control for Mic1-3, line1-2, Mp3/FM, bass/treble and master
- With short-circuit, clip, overload and high temp protection
- AC220V or 115V & 24V DC both operation system

Specification:

Model	FA-30E	FA-60E	FA-120E
Description	Public Address System 60W Mixer Amplifier		
Rated Power Output	30W	60w	120w
Speaker Output	70V, 100V and 4-16Ω		
Input	Mic1-3: 600 ohms(Ω) 5-8 mV, unbalanced, Line1-2: 10k ohms(Ω) 150-470 mV, unbalanced		
Frequency Response	60-15KHz		
THD	<0.5% at 1kHz, 1/3 rated power		
S/N Ratio	Line: 85 dB, MIC: >72 dB		
Protection	High temp, short circuit, overload protection		
Power Supply	AC230V or DC24V, 50-60Hz		
Power Consumption	45W	100W	200W
Dimension	300(W)×275(D)×88(H)mm		
Gross Weight	5.5kg	6.6kg	7.8kg
Warranty	3 years		